

Configuring an LG Xenon for MMS and Browser with a Solo SIM card on the HSPA+ Network

The following instructions can be used to manually configure the settings on an unlocked LG Xenon phone for MMS and Browser with a Solo SIM Card.

1. Follow the instructions in the user manual to install your Solo SIM Card into the phone.
2. Power on the phone.

Browser Settings

Create a profile for the Access Point.

3. On the standby screen, touch the **Menu** icon.
4. Touch the **Settings** icon.
5. Touch **More**.
6. Touch **Connection**.
7. Touch **Access Points**.
8. Touch **New Profile**.
9. Enter the following settings information in each of the fields:
Connection Title: Bell WAP Connection (can be anything)
Authentication: Medium
Username: <leave blank>
Password: <leave blank>
APN: pda.bell.ca
10. Touch **Save**.

Create an Internet Profile.

11. Return back to the **Connection** settings screen, and touch **Internet Profiles**.
12. Touch **New Profile**.
13. Enter the following settings information in each of the fields:
Profile Name: Bell WAP Profile (can be anything)
Use Proxy: ON
Proxy Address: web.wireless.bell.ca
Proxy Port Number: 80
Access Point: select 'Bell WAP Connection' (the Connection Title created above)
14. Touch **Save**.

Set the Browser Account settings.

15. Return back to **Settings**, and touch **More**. 
16. Touch **Application Settings**.
17. Touch **Browser**.
18. Touch **Accounts**.
19. Touch **New Account**.
20. Enter the following settings information in each of the fields:
Account Name: Bell WAP Browser (can be anything)
Homepage: http://homepage
Internet Profile: select 'Bell WAP Profile' (the Internet Profile Name created above)
21. Touch **Save**.
22. A message will be displayed that the setting have been saved, and prompts whether to activate the account. Select **Yes**.

MMS Settings

Create a profile for the Access Point.

23. On the standby screen, touch the **Menu** icon. 

24. Touch the **Settings** icon. 

25. Touch **More**. 

26. Touch **Connection**.

27. Touch **Access Points**.

28. Touch **New Profile**.

29. Enter the following settings information in each of the fields:

Connection Title: Bell MMS Connection (can be anything)

Authentication: Medium

Username: <leave blank>

Password: <leave blank>

APN: pda.bell.ca

30. Touch **Save**.

Create an Internet Profile.

31. Return back to the **Connection** settings screen, and touch **Internet Profiles**.

32. Touch **New Profile**.

33. Enter the following settings information in each of the fields:

Profile Name: Bell MMS Profile (can be anything)

Use Proxy: select ON

Proxy Address: web.wireless.bell.ca

Proxy Port Number: 80

Access Point: select 'Bell MMS Connection' (the Connection Title created above)

34. Touch **Save**.

Set the Message Centre settings.

35. Return back to **Settings**, and touch **More**. 

36. Touch **Application Settings**.

37. Touch **Messaging**.

38. Touch **Multimedia Message**.

39. Touch **Message Centre**.

40. Touch **New Message Centre**.

41. Enter the following settings information in each of the fields:

Name: Bell MMS Connection (can be anything)

MMSC URL: http://mms.bell.ca/mms/wapenc

Internet Profile: select 'Bell MMS Profile' (the Internet Profile Name created above).

42. Touch **Save**.

43. In the New Message Centre box, touch on the name that you created above to select it. Touch **Activate**.