

Configuring a Sony Ericsson K850i for MMS and Browser with a Solo SIM Card on the HSPA+ network

The following instructions can be used to manually configure the settings on an unlocked Sony Ericsson K850i phone for MMS and Browser with a Solo SIM Card.

1. Follow the instructions in the user manual to install your Solo SIM Card into the phone.
2. Power on the phone.

Browser settings

1. From the standby screen, select **Menu > Settings > Connectivity** (navigate right to this tab) > **Internet settings**.
2. Select **Connect using**.
3. Press **Options** (left soft key), and select **Create new**.
4. Select **PS data**.
5. Edit the following settings information into each of the fields:
Name: Bell WAP Connection (can be anything)
APN: pda.bell.ca
6. Press **Save** (left soft key).
7. With the newly created name (Bell WAP Connection) highlighted, press **Options** (left soft key), and select **Edit**.
8. Scroll down to highlight **Proxy settings**, and select **Edit**.
9. Scroll to highlight **Proxy**, select **Edit**, and select **On**.
10. Scroll down to highlight **Proxy servers**, and select **Edit**.
11. Select **HTTP** and edit and save the following settings information into each of the fields:
Username: <leave blank>
Password: <leave blank>
Proxy address: web.wireless.bell.ca
Port: 80
12. Navigate back to the **Data account** screen, scroll and highlight the name you created above (Bell WAP Connection). Press **Select** (middle soft key), and then press **Save** (left soft key).

MMS settings

1. From the standby screen, select **Menu > Settings > Connectivity** (navigate right to this tab) > **Internet settings**.
13. Select **Connect using**.
14. Press **Options** (left soft key), and select **Create new**.
15. Select **PS data**.
16. Edit the following settings information into each of the fields:
Name: Bell MMS Connection (can be anything)
APN: pda.bell.ca
17. Press **Save** (left soft key).
18. With the newly added account name highlighted, press **Options** (left soft key), and select **Edit**.
19. Scroll down to highlight **Authentication**, and select **Edit**.
20. Select (mark) **PAP**, and deselect (unmark) all other options. Press **Save** (left soft key).
21. Scroll down to highlight **Proxy settings**, and select **Edit**.
22. Scroll to highlight **Proxy**, select **Edit**, and select **On**.
23. Scroll down to highlight **Proxy servers**, and select **Edit**.
24. Select **HTTP** and edit and save the following settings information in each of the fields:
Username: <leave blank>
Password: <leave blank>

Proxy address: web.wireless.bell.ca

Port: 80

25. Go back to the previous screen and apply the settings for HTTP to **Secure** and **Streaming**.
26. Press **Back** to save the settings and return to the main screen.
27. Navigate to **Menu > Messages > Settings > Picture message > MMS Profile**, and select **Edit**.
28. Scroll to **New Profile** and press **Add** (middle soft key).
29. Edit the following settings information into each of the fields:
 - MMS profile name:** Bell MMS Profile (can be anything)
 - Message server:** http://mms.bell.ca/mms/wapenc
 - Connect using:** select Bell MMS Connection (created above)
30. Press **Save** (left soft key).
31. Scroll and highlight the MMS profile name that you just created (Bell MMS Profile), and press **Select** (middle key).